MOVING HEAD G10 HYBRID :

DMX channel´s functions and their values (25 DMX channels):

Mode/Channel			Value	Function	
St	Ba	Ex			
				Color Wheel :	
			0-7	Open / white	ώ
			8-19	Color 1	1
			20-31	Color 2	2
			32-43	Color 3	3
			44-55	Color 4	4
			56-67	Color 5	5
1	1	1	68-79	Color 6	6
			80-91	Color 7	7
			92-103	Color 8	8
			104-115	Color 9	9
			116-127	Color 10	10
			128-189	Forwards rainbow effect from fast to slow	ɾ ⌠
			190-193	No rotation	Å
			194-255	Backwards rainbow effect from slow to	ΐ ɾ ⌠
				Color Wheel Fine :	
		2	0-255	Color Wheel colour change to any position Fine	κ β
				Rotating gobos, cont. rotation :	
			0-10	Beam open	Beam تم
			11-21	Spot open	Spot تم
			22-31	Rot. gobo 1	يد 1
			32-41	Rot. gobo 2	يد 2
			42-51	Rot. gobo 3	يد 3
			52-61	Rot. gobo 4	يد 4
			62-71	Rot. gobo 5	يد 5
			72-81	Rot. gobo 6	يد 6
			82-91	Rot. gobo 7	يد 7
			92-101	Rot. gobo 8	يد 8
			102-112	Rot. gobo 2 shake	يد 1 ⌟
2	2	3	113-123	Rot. gobo 3 shake	يد 2 ⌟
			124-134	Rot. gobo 4 shake	يد 3 ⌟
			135-145	Rot. gobo 5 shake	يد 4 ⌟
			146-156	Rot. gobo 6 shake	يد 5 ⌟
			157-167	Rot. gobo 7 shake	يد 6 ⌟
			168-178	Rot. gobo 8 shake	يد 7 ⌟
			179-189	Rot. gobo 9 shake	يد 8 ⌟
			190-221	Gobo wheel rotation forwards from fast to slow	يد ɾ ⌠
			222-223	No rotation	Å
			224-255	Gobo wheel rotation f backwards from slow to fast	يد ΐ ɾ ⌠
				Rotating gobo index, rotating gobo rotation :	
3	3	4	0-127	Gobo indexing	يد β

128-189	Forwards gobo rotation from fast to	
190-193	No rotation	
194-255	Backwards gobo rotation from slow to	
	Rotating gobo indexing Fine	
0-255	Fine indexing	
	Fixed Gobos :	
0-7	Open/hole	
8-14	Gobo 1	1
15-21	Gobo 2	2
22-28	Gobo 3	3
29-35	Gobo 4	4
36-42	Gobo 5	5
43-49	Gobo 6	6
50-56	Gobo 7	

136-143	Macro 2	شي 2
144-151	Macro 3	شي 3
152-159	Macro 4	شي 4
160-167	Macro 5	شي 5
168-175	Macro 6	شي 6
176-183	Macro 7	شي 7
184-191	Macro 8	شي 8
192-199	Macro 9	شي 9
200-207	Macro 10	شي 10
208-215	Macro 11	شي 11
216-223	Macro 12	شي 12
224-231	Macro 13	شي 13
232-239	Macro 14	شي 14
240-247	Macro 15	شي 15
248-255	Macro 16	شي 16
	8 facet rotating prism/Line prism:	
0-127	Prism indexing	Ŭ β
128-189	Forwards prism rotation from fast to slow	ɾ ⌠
190-193	No rotation	Å
194-255	Backwards prism rotation from slow to fast	ĭ h ɾ ⌠
	8 facet rotating prism/Line prism indexing Fine	
0-255	Fine indexing	β ˗
	Focus :	
0-255	Continuous adjustment from near to far	ɾ ⌠
	Focus&Auto Focus Fine:	
0-255	Continuous adjustment Fine	ɾ ⌠ ˗
	Zoom :	
0-255	Zoom adjustment from small to big	ɾ ⌠
	Zoom Fine:	
0-255	Zoom adjustment Fine	ɾ ⌠ ˗
	Shutter, strobe:	
0-31	Shutter closed	˞
32-63	No function (shutter open)	ѽ
64-95	Strobe effect slow to fast	□ ɾ ⌠
96-127	No function (shutter open)	ѽ

Lamp on/off,